



**MODEL 2138** | Specification Sheet  
Commercial Series • Low Voltage • Bollard

TYPE:  MODEL:

PROJECT:

**PRODUCT FEATURES**



Wattage	9 W Max.
Voltage	9 – 15 VAC
Lumens	295 or 389 Lumens
Lamp Type	MR-16 LED
Housing	Copper or Stainless Steel
Dimensions	2 1/8" DIA x 16" H

**ORDERING INFORMATION**

EXAMPLE: **BR-2138-B-4.5-W-36**

**MOUNTING**                      **MODEL**                      **FINISH**                      **LED**  
BR                                      2138

MOUNTING	MODEL	FINISH	LED	ORDERING NOTES
BR ABS Ground Stake	2138	CSN Natural Copper SS Stainless Steel	4.5-W-15 4.5 Watts   Warm   15° Narrow Spot	Fixtures shipped with specified mounting hardware.
			4.5-W-25 4.5 Watts   Warm   25° Spot	
		4.5-W-36 4.5 Watts   Warm   36° Flood		
		4.5-W-60 4.5 Watts   Warm   60° Wide Flood		
		5.5-W-15 5.5 Watts   Warm   15° Narrow Spot		
		5.5-W-25 5.5 Watts   Warm   25° Spot		
		5.5-W-36 5.5 Watts   Warm   36° Flood		
		5.5-W-60 5.5 Watts   Warm   60° Wide Flood		
		NL No Lamp		



**PROFESSIONAL  
OUTDOOR LIGHTING**

www.VistaPro.com • email@vistapro.com • Fax: (888) 670-VISTA (8478)  
1625 Surveyor Avenue • Simi Valley, CA 93063 • (805) 527-0987 • (800) 766-VISTA (8478)

Vista Professional Outdoor Lighting reserves the right to modify the design and/or construction of the fixture shown without further notification.



## SPECIFICATIONS

### CONSTRUCTION:

Heavy-gauge, extruded, copper or stainless steel post fitted with machined solid brass cap.

### LENS:

Clear, machined acrylic lens.

### MOUNTING:

Aluminum mounting base with ABS ground stake included.

### FASTENERS:

All fasteners are stainless steel.

### WIRING:

Prewired with a 36" pigtail of 18-2 direct-burial cable and underground connectors.

### CERTIFICATIONS | STANDARDS | COMPLIANCE:

- UL Certified for wet locations (USA & Canada) | (UL 1838)
- Buy American Act (BAA)
- Build America, Buy America Act (BABA)

### LED:

MR-16 LED Lamp.  
295 or 389 Lumens.  
4.5 or 5.5 Watts.

### ELECTRICAL:

Input voltage range 9 - 15 VAC.  
Low voltage transformer required to operate (sold separately).

## DIMENSIONS

